



- Standalone 1 door controller with built-in EM-Marin card reader and keypad
- Operating frequency: 125 KHz
- Identifiers: EM-Marin card, password, Em-Marin card + password
- Reading distance: up to 100 mm
- Card reader interface: Wiegand 26

Your manual is here:

<http://manuals.partizan.global>



Partizan software:

<http://apps.partizan.global>



Standalone controller with built-in card reader and keypad	
Model	PAR-EK3
Version	Black
Doors	1
Quantity of supported readers	2
Card reader interface	Wiegand 26
Built-in card reader standard	EM-Marin
Built-in card reader frequency	125 KHz
Max quantity of users	1000
Operation mode	Standalone controller/Reader
Interface	
Reading distance, mm	<100
Reading speed, card/s	2
Light indication	+
Sound indication	+
Electric lock output	<20A
Alarm output	<20A
Exit button connect	+
Dimensions	
Size, mm	108x78x22
Weight, g	100
Common	
Power	DC 12V/60mA
Casing material plastic/metal	+/-
Color	Black
IP rating	44
IK rating	-
Operating temperature, °C	0 - +50
Warranty, years	3

*Note: the functions, interface, component parts and the working sequence of the device are subject to alteration without prior notice from the manufacturer due to updates of the device itself as well as its software.

Connection diagram:

