



- Operating frequency: 860-960MHz
- Identifiers: ISO18000-6C
- Reading distance: up to 80 mm
- Output interface: USB 2.0

Reader	
Model	PAR-R1
Version	USB v1.0
Output interface	USB 2.0
Card reader standard	ISO18000-6C
Reader frequency	860-960MHz
Installation method	-
Interface	
Reading distance, mm	<80
Reading speed, card/s	2
Light indication	+
Sound indication	+
Mean time between failures, hours	>10000
Length of USB cable, m	1
Dimensions	
Size, mm	138x88x12
Weight, g	120
Common	
Power	USB 2.0
Casing material plastic/metal	+/-
Color	White
IP rating	44
IK rating	-
Operating temperature, °C	-20 - +60
Warranty, years	3

\*Note: the functions, interface, component parts and the working sequence of the device are subject to alteration without prior notice from the manufacturer due to updates of the device itself as well as its software.

Your manual is here:

<http://manuals.partizan.global>



Partizan software:

<http://apps.partizan.global>

